US009740351B2

(12) **United States Patent**
Li et al.

(10) **Patent No.: US 9,740,351 B2**
(45) **Date of Patent: Aug. 22, 2017**

(54) **MULTI-STEP INCREMENTAL SWITCHING SCHEME**

(71) Applicant: **SYNAPTICS INCORPORATED**, San Jose, CA (US)

(72) Inventors: **Zheming Li**, San Jose, CA (US); **Saikrishna Ganta**, San Jose, CA (US); **Tae-Song Chung**, San Jose, CA (US); **Rafael Betancourt**, Santa Clara, CA (US); **John Michael Weinerth**, San Jose, CA (US); **Farzaneh Shahrokhi**, San Jose, CA (US)

(73) Assignee: **SYNAPTICS INCORPORATED**, San Jose, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 56 days.

(21) Appl. No.: **14/870,243**

(22) Filed: **Sep. 30, 2015**

(65) **Prior Publication Data**

US 2016/0334902 A1 Nov. 17, 2016

Related U.S. Application Data

(60) Provisional application No. 62/162,418, filed on May 15, 2015.

(51) **Int. Cl.**

G09G 5/00	(2006.01)
G06F 3/044	(2006.01)
G06F 3/01	(2006.01)
G06F 3/041	(2006.01)

(52) **U.S. Cl.**

CPC ***G06F 3/044*** (2013.01); ***G06F 3/016*** (2013.01); ***G06F 3/0416*** (2013.01); *G06F 2203/04108* (2013.01)

(58) **Field of Classification Search**

CPC G06F 3/044; G06F 3/016; G06F 3/0416; G06F 2203/04108

USPC 345/174; 178/18.06

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,862,136	A	8/1989	Birkner	
5,117,206	A	5/1992	Imamura	
6,958,661	B2	10/2005	Thompson et al.	
7,300,807	B2	11/2007	Coolbaugh et al.	
7,411,774	B2	8/2008	Leeper, II	
7,566,946	B2	7/2009	Coolbaugh et al.	
8,183,959	B2	5/2012	Katta	
8,288,965	B1	10/2012	Gordin	
8,559,207	B2	10/2013	Kim et al.	
2011/0310054	A1 *	12/2011	Souchkov	G06F 3/044 345/174

FOREIGN PATENT DOCUMENTS

WO	2013154797	A1	10/2013
WO	2014129317	A1	8/2014

* cited by examiner

Primary Examiner — Jennifer Nguyen

(74) *Attorney, Agent, or Firm* — Patterson + Sheridan, LLP

(57) **ABSTRACT**

A capacitance measurement circuit cancels background capacitance while reducing charge leakage and supply ripples during reset phases and integrate phases. The capacitance measurement circuit operates a first switch into a linear mode causing a first resistance in the first switch, and after a delay, operates a second switch into a saturation mode causing a second resistance in parallel to the first resistance.

20 Claims, 8 Drawing Sheets



INTEGRATE PHASE


100
140
150
110
ELECTRONIC SYSTEM
PROCESSING SYSTEM
120
130
130

FIG. 1


120
220
220-1
220-2
220-3
220-n
210-1
210-2
210-3
210-n
210
PROCESSING SYSTEM 110
SENSOR MODULE 202
DETERMINATION MODULE 204
OTHER MODULE(S) 208

FIG. 2



RESET PHASE

FIG. 3A



INTEGRATE PHASE

FIG. 3B


400
406
412
410
C_{FB1}
422
V_{RX}
314
FB_conn_en
Delayed FB_conn_en
CONTROL MODULE 426
424
404
C_{FB0}
408
420
C_B
V_{ref}
V_{OUT}
402

FIG. 4


500
RESET A FEEDBACK CAPACITOR OF THE CHARGE INTEGRATOR TO A FIRST VOLTAGE LEVEL
502
OPEN SWITCHES BETWEEN THE FEEDBACK CAPACITOR AND THE OUTPUT OF THE DIFFERENTIAL AMPLIFIER
504
COUPLE A SENSOR ELECTRODE AND THE FIRST INPUT OF THE DIFFERENTIAL AMPLIFIER TO INITIATE A MEASUREMENT PHASE
506
CLOSE A FIRST SWITCH BETWEEN THE FEEDBACK CAPACITOR AND THE OUTPUT OF THE DIFFERENTIAL AMPLIFIER
508
CLOSE A REMINDER OF THE SWITCHES AFTER A DELAY FROM CLOSING THE FIRST SWITCH
510
OPERATE THE DIFFERENTIAL AMPLIFIER TO INTEGRATE CHARGE ON THE SENSOR ELECTRODE
512

FIG. 5


Cap2 614
Fb_cap_conn<2>
Cap1 612
Fb_cap_conn<1>
Cap0 610
Fb_cap_conn<0>
608
604
C_{FB0}
602
V_{OUT}
V_{ref}
C_B

FIG. 6B


600
Cap2 614
Fb_cap_conn<2>
Cap1 612
Fb_cap_conn<1>
Cap0 610
Fb_cap_conn<0>
608
604
C_{FB0}
602
V_{OUT}
V_{ref}
606
620
C_B

FIG. 6A


614
Cap2
Cap1
Cap0
Fb_cap_conn<2>
Fb_cap_conn<1>
Fb_cap_conn<0>
608
604
C_{FB0}
602
V_{OUT}
V_{ref}
C_B

FIG. 6D


Cap2
Cap1
612
Cap0
Fb_cap_conn<2>
Fb_cap_conn<1>
Fb_cap_conn<0>
608
604
C_{FB0}
602
V_{OUT}
V_{ref}
C_B

FIG. 6C


700
Input
Buffer
710
702
704
R1
706
R2
712
Sw2
708
R3
714
Sw1
716
C1
CURRENT CONVEYOR 720
CURRENT AMPLIFIER 730
TO CHANGE INTEGRATOR

FIG. 7


800
I
V
(R1+R2+R3)
t_{half}

FIG. 8


900
VDDA (+3V)
CP Switch
CP Switch
M10
M11
CLK_NEG1
Cf2
C6
Cap_Top2
Cap_Top1
C5
Cf1
(0V -> +3V)
CLK1
902
VDDA
M18
M19
M20
M21
GND
904
M12
M13
M15
M16
GND
M8
M7
CP Switch
CP Switch
(+6V) CP_OUT
C8
R1
C7
R1
C10
R3
GND
C9
R2
I169
out
inv_3v
in
I1
out
inv_3v
in
910
CLK

FIG. 9

MULTI-STEP INCREMENTAL SWITCHING SCHEME

CROSS-REFERENCE TO RELATED APPLICATIONS

This application claims benefit of U.S. Provisional Patent Application No. 62/162,418, filed May 15, 2015, entitled "Multi-Step Charger Sharing Technique for Global Coarse Baseline Correction" which is incorporated by reference herein.

BACKGROUND

Field of the Disclosure

Embodiments generally relate to input sensing and, in particular, to capacitance sensing.

Description of the Related Art

Input devices including proximity sensor devices (also commonly called touchpads or touch sensor devices) are widely used in a variety of electronic systems. A proximity sensor device typically includes a sensing region, often demarked by a surface, in which the proximity sensor device determines the presence, location, and/or motion of one or more input objects. Proximity sensor devices may be used to provide interfaces for the electronic system. For example, proximity sensor devices are often used as input devices for larger computing systems (such as opaque touchpads integrated in, or peripheral to, notebook or desktop computers). Proximity sensor devices are also often used in smaller computing systems (such as touch screens integrated in cellular phones).

SUMMARY

Embodiments of the present disclosure provide a processing system for a capacitive sensing device. The processing system includes a capacitance measurement circuit configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode. The capacitance measurement circuit includes a differential amplifier having a first input coupled to the sensor electrode, a second input, and an output, and a feedback capacitor coupled between the first input of the differential amplifier and the output of the differential amplifier. The capacitance measurement circuit further includes a first switch and a second switch coupled between the feedback capacitor and the output of the differential amplifier in series. The capacitance measurement circuit includes a control module configured to turn on the first switch and apply a first resistance value in series with the feedback capacitor. The control module is further configured to, after a time delay, turn on the second switch and placing a second resistance in parallel with the first resistance, which lowers a total resistance in series with the feedback capacitor

Another embodiment of the present disclosure provides a processing system for a capacitive sensing device. The processing system includes a capacitance measurement circuit configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode. The capacitance measurement circuit includes a differential amplifier having a first input coupled to the sensor electrode, a second input, and an output. The capacitance measurement circuit includes a first feedback capacitance coupled between the first input of the differential amplifier and the output of the differential amplifier, and a second feedback capacitance coupled in parallel to the first feedback capacitance. The second feedback capacitance includes a plurality of capacitors in series with a plurality of associated switches. The capacitance measurement circuit further includes a control module configured to, during an integrate phase, control each switch of the plurality of switches to couple the associated capacitor to the output of the differential amplifier after a sequential delay.

In another embodiment of the present disclosure, a method of capacitance measurement is provided. The method includes resetting a feedback capacitor of a capacitance measurement circuit to a first voltage level, and opening a plurality of switches between the feedback capacitor and the output of the differential amplifier. The feedback capacitor is coupled between the first input of a differential amplifier and an output of the differential amplifier. The method further includes coupling a sensor electrode and the first input of the differential amplifier to initiate a measurement phase, and closing a first switch of the plurality of switches between the feedback capacitor and the output of the differential amplifier. The method includes closing a remainder of the plurality of switches after a delay from closing the first switch, and operating the differential amplifier to integrate charge on the sensor electrode, such that an absolute capacitance corresponding to a coupling between the sensor electrode and an input object is measured.

BRIEF DESCRIPTION OF THE DRAWINGS

So that the manner in which the above recited features of embodiments can be understood in detail, a more particular description of embodiments, briefly summarized above, may be had by reference to embodiments, some of which are illustrated in the appended drawings. It is to be noted, however, that the appended drawings illustrate only typical embodiments and are therefore not to be considered limiting of scope, for other effective embodiments may be admitted.

FIG. **1** is a block diagram of a system that includes an input device according to an example.

FIG. **2** is a block diagram depicting a capacitive sensor device according to an embodiment of the present disclosure.

FIGS. **3**A-**3**B illustrate operation of a capacitance measurement circuit through a cycle of absolute capacitive sensing, including a reset phase and an integration phase, according to an embodiment of the present disclosure.

FIG. **4** is a circuit diagram of a capacitance measurement circuit configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode, according to an embodiment.

FIG. **5** is a flow diagram illustrating a method for measuring capacitance with a charge integrator, according to an embodiment.

FIGS. **6**A-**6**D illustrate operation of a capacitance measurement circuit through a cycle of absolute capacitive sensing, including a reset phase and an integration phase, according to an embodiment of the present disclosure.

FIG. **7** is a block diagram depicting a circuit for generating a charge, according to one embodiment of the present disclosure.

FIG. **8** is a chart diagram depicting a current input waveform, according to one embodiment of the present disclosure.

FIG. **9** is a block diagram depicting a charge pump circuit using the described switching scheme, according to one embodiment of the present disclosure.

To facilitate understanding, identical reference numerals have been used, where possible, to designate identical

elements that are common to the figures. It is contemplated that elements of one embodiment may be beneficially incorporated in other embodiments.

DETAILED DESCRIPTION

The following detailed description is merely exemplary in nature and is not intended to limit the embodiments or the application and uses of such embodiments. Furthermore, there is no intention to be bound by any expressed or implied theory presented in the preceding technical field, background, brief summary or the following detailed description.

Turning now to the figures, FIG. **1** is a block diagram of an exemplary input device **100**, in accordance with embodiments of the invention. The input device **100** may be configured to provide input to an electronic system (not shown). As used in this document, the term "electronic system" (or "electronic device") broadly refers to any system capable of electronically processing information. Some non-limiting examples of electronic systems include personal computers of all sizes and shapes, such as desktop computers, laptop computers, netbook computers, tablets, web browsers, e-book readers, and personal digital assistants (PDAs). Additional example electronic systems include composite input devices, such as physical keyboards that include input device **100** and separate joysticks or key switches. Further example electronic systems include peripherals such as data input devices (including remote controls and mice), and data output devices (including display screens and printers). Other examples include remote terminals, kiosks, and video game machines (e.g., video game consoles, portable gaming devices, and the like). Other examples include communication devices (including cellular phones, such as smart phones), and media devices (including recorders, editors, and players such as televisions, set-top boxes, music players, digital photo frames, and digital cameras). Additionally, the electronic system could be a host or a slave to the input device.

The input device **100** can be implemented as a physical part of the electronic system or can be physically separate from the electronic system. As appropriate, the input device **100** may communicate with parts of the electronic system using any one or more of the following: buses, networks, and other wired or wireless interconnections. Examples include I^2C, SPI, PS/2, Universal Serial Bus (USB), Bluetooth, RF, and IRDA.

In FIG. **1**, the input device **100** is shown as a proximity sensor device (also often referred to as a "touchpad" or a "touch sensor device") configured to sense input provided by one or more input objects **140** in a sensing region **120**. Example input objects include fingers and styli, as shown in FIG. **1**.

Sensing region **120** encompasses any space above, around, in, and/or near the input device **100** in which the input device **100** is able to detect user input (e.g., user input provided by one or more input objects **140**). The sizes, shapes, and locations of particular sensing regions may vary widely from embodiment to embodiment. In some embodiments, the sensing region **120** extends from a surface of the input device **100** in one or more directions into space until signal-to-noise ratios prevent sufficiently accurate object detection. The distance to which this sensing region **120** extends in a particular direction, in various embodiments, may be on the order of less than a millimeter, millimeters, centimeters, or more, and may vary significantly with the type of sensing technology used and the accuracy desired. Thus, some embodiments sense input that comprises no contact with any surfaces of the input device **100**, contact with an input surface (e.g., a touch surface) of the input device **100**, contact with an input surface of the input device **100** coupled with some amount of applied force or pressure, and/or a combination thereof. In various embodiments, input surfaces may be provided by surfaces of casings within which the sensor electrodes reside, by face sheets applied over the sensor electrodes or any casings, etc. In some embodiments, the sensing region **120** has a rectangular shape when projected onto an input surface of the input device **100**.

The input device **100** may utilize any combination of sensor components and sensing technologies to detect user input in the sensing region **120**. The input device **100** comprises one or more sensing elements for detecting user input. As several non-limiting examples, the input device **100** may use capacitive, elastive, resistive, inductive, magnetic, acoustic, ultrasonic, and/or optical techniques. Some implementations are configured to provide images that span one, two, three, or higher dimensional spaces. Some implementations are configured to provide projections of input along particular axes or planes. In some resistive implementations of the input device **100**, a flexible and conductive first layer is separated by one or more spacer elements from a conductive second layer. During operation, one or more voltage gradients are created across the layers. Pressing the flexible first layer may deflect it sufficiently to create electrical contact between the layers, resulting in voltage outputs reflective of the point(s) of contact between the layers. These voltage outputs may be used to determine positional information.

In some inductive implementations of the input device **100**, one or more sensing elements pick up loop currents induced by a resonating coil or pair of coils. Some combination of the magnitude, phase, and frequency of the currents may then be used to determine positional information.

In some capacitive implementations of the input device **100**, voltage or current is applied to create an electric field. Nearby input objects cause changes in the electric field and produce detectable changes in capacitive coupling that may be detected as changes in voltage, current, or the like.

Some capacitive implementations utilize arrays or other regular or irregular patterns of capacitive sensing elements to create electric fields. In some capacitive implementations, separate sensing elements may be ohmically shorted together to form larger sensor electrodes. Some capacitive implementations utilize resistive sheets, which may be uniformly resistive.

Some capacitive implementations utilize "self capacitance" (or "absolute capacitance") sensing methods based on changes in the capacitive coupling between sensor electrodes and an input object. In various embodiments, an input object near the sensor electrodes alters the electric field near the sensor electrodes, changing the measured capacitive coupling. In one implementation, an absolute capacitance sensing method operates by modulating sensor electrodes with respect to a reference voltage (e.g., system ground) and by detecting the capacitive coupling between the sensor electrodes and input objects.

Some capacitive implementations utilize "mutual capacitance" (or "transcapacitance") sensing methods based on changes in the capacitive coupling between sensor electrodes. In various embodiments, an input object near the sensor electrodes alters the electric field between the sensor electrodes, changing the measured capacitive coupling. In one implementation, a transcapacitive sensing method operates by detecting the capacitive coupling between one or

more transmitter sensor electrodes (also "transmitter electrodes" or "transmitters") and one or more receiver sensor electrodes (also "receiver electrodes" or "receivers"). Transmitter sensor electrodes may be modulated relative to a reference voltage (e.g., system ground) to transmit transmitter signals. Receiver sensor electrodes may be held substantially constant relative to the reference voltage to facilitate receipt of resulting signals. A resulting signal may comprise effect(s) corresponding to one or more transmitter signals and/or to one or more sources of environmental interference (e.g., other electromagnetic signals). Sensor electrodes may be dedicated transmitters or receivers, or sensor electrodes may be configured to both transmit and receive. Alternatively, the receiver electrodes may be modulated relative to ground.

In FIG. **1**, a processing system **110** is shown as part of the input device **100**. The processing system **110** is configured to operate the hardware of the input device **100** to detect input in the sensing region **120**. The processing system **110** comprises parts of, or all of, one or more integrated circuits (ICs) and/or other circuitry components. For example, a processing system for a mutual capacitance sensor device may comprise transmitter circuitry configured to transmit signals with transmitter sensor electrodes and/or receiver circuitry configured to receive signals with receiver sensor electrodes. In some embodiments, the processing system **110** also comprises electronically-readable instructions, such as firmware code, software code, and/or the like. In some embodiments, components composing the processing system **110** are located together, such as near sensing element(s) of the input device **100**. In other embodiments, components of processing system **110** are physically separate with one or more components close to sensing element(s) of input device **100** and one or more components elsewhere. For example, the input device **100** may be a peripheral coupled to a desktop computer, and the processing system **110** may comprise software configured to run on a central processing unit of the desktop computer and one or more ICs (perhaps with associated firmware) separate from the central processing unit. As another example, the input device **100** may be physically integrated in a phone, and the processing system **110** may comprise circuits and firmware that are part of a main processor of the phone. In some embodiments, the processing system **110** is dedicated to implementing the input device **100**. In other embodiments, the processing system **110** also performs other functions, such as operating display screens, driving haptic actuators, etc.

The processing system **110** may be implemented as a set of modules that handle different functions of the processing system **110**. Each module may comprise circuitry that is a part of the processing system **110**, firmware, software, or a combination thereof. In various embodiments, different combinations of modules may be used. Example modules include hardware operation modules for operating hardware such as sensor electrodes and display screens, data processing modules for processing data such as sensor signals and positional information, and reporting modules for reporting information. Further example modules include sensor operation modules configured to operate sensing element(s) to detect input, identification modules configured to identify gestures such as mode changing gestures, and mode changing modules for changing operation modes.

In some embodiments, the processing system **110** responds to user input (or lack of user input) in the sensing region **120** directly by causing one or more actions. Example actions include changing operation modes, as well as GUI actions such as cursor movement, selection, menu navigation, and other functions. In some embodiments, the processing system **110** provides information about the input (or lack of input) to some part of the electronic system (e.g., to a central processing system of the electronic system that is separate from the processing system **110**, if such a separate central processing system exists). In some embodiments, some part of the electronic system processes information received from the processing system **110** to act on user input, such as to facilitate a full range of actions, including mode changing actions and GUI actions.

For example, in some embodiments, the processing system **110** operates the sensing element(s) of the input device **100** to produce electrical signals indicative of input (or lack of input) in the sensing region **120**. The processing system **110** may perform any appropriate amount of processing on the electrical signals in producing the information provided to the electronic system. For example, the processing system **110** may digitize analog electrical signals obtained from the sensor electrodes. As another example, the processing system **110** may perform filtering or other signal conditioning. As yet another example, the processing system **110** may subtract or otherwise account for a baseline, such that the information reflects a difference between the electrical signals and the baseline. As yet further examples, the processing system **110** may determine positional information, recognize inputs as commands, recognize handwriting, and the like.

"Positional information" as used herein broadly encompasses absolute position, relative position, velocity, acceleration, and other types of spatial information. Exemplary "zero-dimensional" positional information includes near/far or contact/no contact information. Exemplary "one-dimensional" positional information includes positions along an axis. Exemplary "two-dimensional" positional information includes motions in a plane. Exemplary "three-dimensional" positional information includes instantaneous or average velocities in space. Further examples include other representations of spatial information. Historical data regarding one or more types of positional information may also be determined and/or stored, including, for example, historical data that tracks position, motion, or instantaneous velocity over time.

In some embodiments, the input device **100** is implemented with additional input components that are operated by the processing system **110** or by some other processing system. These additional input components may provide redundant functionality for input in the sensing region **120** or some other functionality. FIG. **1** shows buttons **130** near the sensing region **120** that can be used to facilitate selection of items using the input device **100**. Other types of additional input components include sliders, balls, wheels, switches, and the like. Conversely, in some embodiments, the input device **100** may be implemented with no other input components.

In some embodiments, the input device **100** comprises a touch screen interface, and the sensing region **120** overlaps at least part of an active area of a display screen. For example, the input device **100** may comprise substantially transparent sensor electrodes overlaying the display screen and provide a touch screen interface for the associated electronic system. The display screen may be any type of dynamic display capable of displaying a visual interface to a user, and may include any type of light emitting diode (LED), organic LED (OLED), cathode ray tube (CRT), liquid crystal display (LCD), plasma, electroluminescence (EL), or other display technology. The input device **100** and the display screen may share physical elements. For

example, some embodiments may utilize some of the same electrical components for displaying and sensing. As another example, the display screen may be operated in part or in total by the processing system **110**.

It should be understood that while many embodiments of the invention are described in the context of a fully functioning apparatus, the mechanisms of the present invention are capable of being distributed as a program product (e.g., software) in a variety of forms. For example, the mechanisms of the present invention may be implemented and distributed as a software program on information bearing media that are readable by electronic processors (e.g., non-transitory computer-readable and/or recordable/writable information bearing media readable by the processing system **110**). Additionally, the embodiments of the present invention apply equally regardless of the particular type of medium used to carry out the distribution. Examples of non-transitory, electronically readable media include various discs, memory sticks, memory cards, memory modules, and the like. Electronically readable media may be based on flash, optical, magnetic, holographic, or any other storage technology.

FIG. **2** shows one embodiment of the input device **100** with a portion of an example sensor electrode pattern configured to sense in the sensing region **120** associated with the pattern, according to some embodiments. For clarity of illustration and description, FIG. **2** depicts a sensor pattern as a plurality of simple rectangles, though it is understood that the array may have other geometric forms and/or various components not shown. This sensor electrode pattern comprises a first plurality of sensor electrodes **210** (**210-1**, **210-2**, **210-3**, . . . **210-*n***), and a second plurality of sensor electrodes **220** (**220-1**, **220-2**, **220-3**, . . . **220-*n***) disposed over the first plurality of sensor electrodes **210**.

The sensor electrodes **210**, **220** are typically ohmically isolated from one another. Additionally, where a sensor electrode **210** includes multiple sub-electrodes, the sub-electrodes may be ohmically isolated from each other. In one embodiment, all of the sensor electrodes **210** can be disposed on a single layer of a substrate. While the sensor electrodes are shown disposed on a single substrate, in some embodiments, the sensor electrodes can be disposed on more than one substrate. For example, some sensor electrodes can be disposed on a first substrate, and other sensor electrodes can be disposed on a second substrate adhered to the first substrate.

In general, the processing system **110** excites or drives sensing elements of the sensor electrode pattern with a sensing signal and measures an induced or resulting signal that includes the sensing signal and effects of input in the sensing region **120**. The terms "excite" and "drive" as used herein encompasses controlling some electrical aspect of the driven element. For example, it is possible to drive current through a wire, drive charge into a conductor, drive a substantially constant or varying voltage waveform onto an electrode, etc. A sensing signal can be constant, substantially constant, or varying over time, and generally includes a shape, frequency, amplitude, and phase. A sensing signal can be referred to as an "active signal" as opposed to a "passive signal," such as a ground signal or other reference signal. A sensing signal can also be referred to as a "transmitter signal" when used in transcapacitive sensing, or an "absolute sensing signal" or "modulated signal" when used in absolute sensing.

In an example, the processing system **110** drives sensing element(s) of the sensor electrode pattern with a voltage and senses resulting respective charge on sensing element(s). That is, the sensing signal is a voltage signal and the resulting signal is a charge signal (e.g., a signal indicative of accumulated charge, such as an integrated current signal). Capacitance is proportional to applied voltage and inversely proportional to accumulated charge. The processing system **110** can determine measurement(s) of capacitance from the sensed charge. In another example, the processing system **110** drives sensing element(s) of the sensor electrode pattern with charge and senses resulting respective voltage on sensing element(s). That is, the sensing signal is a signal to cause accumulation of charge (e.g., current signal) and the resulting signal is a voltage signal. The processing system **110** can determine measurement(s) of capacitance from the sensed voltage. In general, the term "sensing signal" is meant to encompass both driving voltage to sense charge and driving charge to sense voltage, as well as any other type of signal that can be used to obtain indicia of capacitance. "Indicia of capacitance" include measurements of charge, current, voltage, and the like, from which capacitance can be derived.

The processing system **110** can include a sensor module **202** and a determination module **204**. The sensor module **202** and the determination module **204** comprise modules that perform different functions of the processing system **110**. In other examples, different configurations of one or more other modules **206** can perform the functions described herein. The sensor module **202** and the determination module **204** can include circuitry and can also include firmware, software, or a combination thereof operating in cooperation with the circuitry.

The sensor module **202** selectively drives sensing signal(s) on one or more sensing elements of the sensor electrode pattern over one or more cycles ("excitation cycles") in accordance with one or more schemes ("excitation schemes"). During each excitation cycle, the sensor module **202** can selectively sense resulting signal(s) from one or more sensing elements of the sensor electrode pattern. Each excitation cycle has an associated time period during which sensing signals are driven and resulting signals measured.

In one type of excitation scheme, the sensor module **202** can selectively drive sensing elements of the sensor electrode pattern for absolute capacitive sensing. In absolute capacitive sensing, the sensor module **202** can measure voltage, charge, or current on sensor electrode(s) **210**, **220** to obtain resulting signals indicative of a capacitance between the sensor electrode(s) **210**, **220** and an input object. In such an excitation scheme, measurements of absolute capacitance between the selected sensing element(s) and input object(s) are determined from the resulting signal(s).

In another type of excitation scheme, the sensor module **202** can selectively drive sensing elements of the sensor electrode pattern for transcapacitive sensing. In transcapacitive sensing, the sensor module **202** drives selected transmitter sensor electrodes with transmitter signal(s) and senses resulting signals from selected receiver sensor electrodes. In such an excitation scheme, measurements of transcapacitance between transmitter and receiver electrodes are determined from the resulting signals. In an example, the sensor module **202** can drive selected sensor electrodes **210** with transmitter signal(s), and receive resulting signals from the sensor electrodes **220**.

In any excitation cycle, the sensor module **202** can drive sensing elements of the sensor electrode pattern with other signals, including reference signals and guard signals. That is, those sensing elements of the sensor electrode pattern that are not driven with a sensing signal, or sensed to receive

resulting signals, can be driven with a reference signal, a guard signal, or left floating (i.e., not driven with any signal). A reference signal can be a ground signal (e.g., system ground) or any other constant or substantially constant voltage signal. A guard signal can be a signal that is similar or the same in at least one of shape, amplitude, frequency, or phase of a transmitter signal.

"System ground" may indicate a common voltage shared by system components. For example, a capacitive sensing system of a mobile phone can, at times, be referenced to a system ground provided by the phone's power source (e.g., a charger or battery). The system ground may not be fixed relative to earth or any other reference. For example, a mobile phone on a table usually has a floating system ground. A mobile phone being held by a person who is strongly coupled to earth ground through free space may be grounded relative to the person, but the person-ground may be varying relative to earth ground. In many systems, the system ground is connected to, or provided by, the largest area electrode in the system. The capacitive sensor device **200** can be located proximate to such a system ground electrode (e.g., located above a ground plane or backplane).

The determination module **204** performs capacitance measurements based on resulting signals obtained by the sensor module **202**. The capacitance measurements can include changes in capacitive couplings between elements (also referred to as "changes in capacitance"). For example, the determination module **204** can determine baseline measurements of capacitive couplings between elements without the presence of input object(s). The determination module **204** can then combine the baseline measurements of capacitive couplings with measurements of capacitive couplings in the presence of input object(s) to determine changes in capacitive couplings.

In an example, the determination module **204** can perform a plurality of capacitance measurements associated with specific portions of the sensing region **120** as "capacitive pixels" to create a "capacitive image" or "capacitive frame." A capacitive pixel of a capacitive image represents a location within the sensing region **120** in which a capacitive coupling can be measured using sensing elements of the sensor electrode pattern. For example, a capacitive pixel can correspond to a transcapacitive coupling between a sensor electrode **210-1** and another sensor electrode **220-1** affected by input object(s). In another example, a capacitive pixel can correspond to an absolute capacitance of a sensor electrode **210** or **220**. The determination module **204** can determine an array of capacitive coupling changes using the resulting signals obtained by the sensor module **202** to produce an x-by-y array of capacitive pixels that form a capacitive image. The capacitive image can be obtained using transcapacitive sensing (e.g., transcapacitive image), or obtained using absolute capacitive sensing (e.g., absolute capacitive image). In this manner, the processing system **110** can capture a capacitive image that is a snapshot of the response measured in relation to input object(s) in the sensing region **120**. A given capacitive image can include all of the capacitive pixels in the sensing region, or only a subset of the capacitive pixels.

In another example, the determination module **204** can perform a plurality of capacitance measurements associated with a particular axis of the sensing region **120** to create a "capacitive profile" along that axis. For example, the determination module **204** can determine an array of absolute capacitive coupling changes along an axis defined by the sensor electrodes **210**-N and/or the sensor electrodes **220**-N to produce capacitive profile(s). The array of capacitive coupling changes can include a number of points less than or equal to the number of sensor electrodes along the given axis.

Measurement(s) of capacitance by the processing system **110**, such as capacitive image(s) or capacitive profile(s), enable the sensing of contact, hovering, or other user input with respect to the formed sensing regions by the sensor electrode pattern. The determination module **204** can utilize the measurements of capacitance to determine positional information with respect to a user input relative to the sensing regions formed by the sensor electrode pattern. The determination module **204** can additionally or alternatively use such measurement(s) to determine input object size and/or input object type.

In one or more embodiments, the processing system **110** may be configured to operate the capacitive sensor device to perform a type of proximity sensing sometimes referred as "hover" sensing (in contrast to sensing by actual touch). However, to achieve acceptable performance in hover sensing, the processing system **110** is configured to be able to obtain small, incremental background capacitance measurements. To amplify signals processed by the processing system **110**, the processing system gains up the signals before performing analog-to-digital conversion. However, the pre-conversion signals may have a large range depending on the proximity of input object (e.g., finger) and on the amount of background capacitance. As such, the processing system **110** is configured to perform background capacitance cancellation to prevent saturation of internal stages within the processing system **110**.

One effective method is to use feedback capacitance in an integrator's feedback to effectuate background capacitance cancellation. As described in greater detail later, the sensor module **202** charges the feedback capacitors during the reset phase to a reference voltage and such charge effectively cancels the background capacitance. However, this technique introduces large charge leakage into the integrator because the input node of the integrators goes above and below supply rails. Also, the sudden discharge of capacitance can cause "supply ripples" and power supply rejection (PSR) issues, particularly in single-ended systems. Accordingly, embodiments of the present disclosure provide various systems and switching schemes for resolving the above-described problems.

Another method for cancelling background capacitance is to add an opposite polarity charge on the background capacitance. As further described later, the sensor module **202** includes a capacitor whose one end is coupled to C_B (i.e., capacitance to ground) and the other end is excited by a voltage signal having an opposite polarity. To reduce the physical size of such a described capacitor, the sensor module **202** can output the charge into a current conveyor followed by a current amplifier whose output is connected to C_B. Nonetheless, the physical size of the capacitor used by the described method may pose severe restrictions on bandwidth and performance of the current amplifier. Accordingly, embodiments of the present disclosure provide a multi-step charge shaping technique to be used for background capacitance, which further reduces the specification imposed on the current amplifier.

FIGS. **3**A-**3**B illustrate operation of a capacitance measurement circuit **300** through a cycle of absolute capacitive sensing, including a reset phase (FIG. **3**A) and an integration phase (FIG. **3**B), according to an embodiment. The capacitance measurement circuit **300** may be included as part of an input device **100** and/or the processing system **110**. For example, the processing system **110** may supply input volt-

ages for the circuit **300** as well as control signals which operate switches in the circuit **300** and/or select capacitors from a bank of selectable capacitors. In one embodiment, the capacitance measurement circuit **300** includes a differential amplifier **302** with inverting and non-inverting inputs and an output (V_{OUT}). A first switch **320** is coupled between the non-inverting input of the differential amplifier **302** and a sensor electrode, such as sensor electrodes **210**, **220** described above with respect to FIG. **2**, to which circuit **300** is coupled.

The differential amplifier **302** is configured as a charge integrator and includes a feedback capacitance (C_{FB}) disposed between the output and the inverting input. The feedback capacitance is represented by one or more capacitors that are coupled on one side (e.g., a node **312**) to the output of the differential amplifier **302** and coupled on the other side (e.g., a node **310**) to the inverting input of the differential amplifier **302**. In the depicted embodiment, the feedback capacitance C_{FB} is split into multiple feedback capacitors, e.g., a first feedback capacitor **304** (C_{FB0}) and a second feedback capacitor **306** (C_{FB1}), such that one capacitor **304** can be reset while the other capacitor **306** is pre-charged to either a reference voltage V_{RX} or ground during a pre-charge/reset phase of a sensing cycle. This pre-charge of the feedback capacitor works to cancel background capacitance as mentioned above. The selection of whether the feedback capacitor **306** is pre-charged to the reference voltage or ground is accomplished by the position of a switch **314** during the pre-charge/reset phase of a sensing cycle.

A switch **308** is disposed in parallel to the feedback capacitors **304**, **306**. The switch **308** operates as a reset mechanism to discharge and reset the feedback capacitors **304**, **306**. In FIGS. **3**A and **3**B, capacitance C_B represents a background capacitance, which may include capacitance contributed to by an input object **140**, between a sensor electrode and ground.

In operation, the capacitance measurement circuit **300** performs an absolute sensing method having the differential amplifier **302** is set up as a charge integrator and a reference voltage is applied to the non-inverting input of the differential amplifier **302**. In one embodiment, the reference voltage is modulated by substantially equal amounts above and below a reference voltage (i.e., ΔV_{REF}), which in some embodiments is approximately on half of a supply voltage V_{RX}. As such, the voltage applied to the non-inverting input is depicted as a first voltage ($V_{RX}/2+\Delta V_{REF}$).

During a reset phase of a (first half) sensing cycle, which is depicted in FIG. **3**A, the switch **320** is opened to decouple the circuit **300** from the sensor electrode, the first feedback capacitor **304** is discharged by closing the switch **308**, and the second feedback capacitor **306** is pre-charged to a voltage level by operating the switch **314** to be coupled to ground. During an integrate phase of the sensing cycle, which is depicted in FIG. **3**B, the feedback capacitors **304**, **306** are placed in parallel by coupling switch **314** with the output V_{OUT} of the differential amplifier **302** and opening the switch **308**. The inverting input of the differential amplifier **302** is coupled to the background capacitance C_B by closing the first switch **320**.

In conventional capacitance measurement circuits, in the reset phase, the voltage level on one side of the feedback capacitor (e.g., at the node **312**) is 0 V. In the integrate phase, that side of the feedback capacitor is coupled to a reference voltage ($V_{RX}/2+\Delta V_{REF}$). An insert in FIG. **3**B includes a line graph **350** depicting the sudden step from 0V to $V_{RX}/2+\Delta V_{REF}$ at node **312**, which causes the first node **310** to "exceed rails." Another insert in FIG. **3**B includes a line graph **340** depicting the voltage level at the other side of the feedback capacitor **306** (e.g., a node **310**), which exceeds the supply voltage level **144**. This excess voltage causes charge leakage via reverse biased diodes and the feedback switch **308** in the capacitance measurement circuit **300** until the differential amplifier **302** reacts and brings back the first node **310** to the voltage level $V_{RX}/2+\Delta V_{REF}$. Such RC characteristics can cause a significant error in the reference voltages, i.e., the settled final output voltage of the amplifier, yielding wrong ADC results and are a non-linear function of the input capacitor C_B.

Accordingly, one or more embodiments of the present disclosure are configured to reduce the voltage spike occurring at the inverting input of the differential amplifier **302** of the capacitance measurement circuit **300** when transitioning from the reset phase to the integrate phase. In one embodiment, the capacitance measurement circuit **300** includes a "ramp" mechanism which delays the voltage peaking to provide the differential amplifier **302** an opportunity to correct the input node back to V_{REF}.

In one embodiment, the capacitance measurement circuit **300** includes a resistor **316** coupled between one side of the feedback capacitor **306** and the output V_{OUT} of the differential amplifier **302**. The resistor **316** is configured to create a ramp at the node **310** from 0 V to the reference voltage when moving from the reset phase to the integrate phase during a time period T_{REACT}, which represents a time duration sufficient to permit the differential amplifier **302** to correct the input node **310** back to the reference voltage.

FIG. **4** is a circuit diagram of a capacitance measurement circuit **400** configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode, according to an embodiment. In some cases, the use of a fixed resistor as depicted in FIG. **4** may alter the settling response of the differential amplifier and the capacitance measurement circuit as a whole, because the resistor would always be in series to the feedback capacitor. The capacitance measurement circuit **400** is configured to address such issues. Similar to the capacitance measurement circuit **300**, the circuit **400** may be included as part of an input device **100** and/or the processing system **110**. For example, the processing system **110** may supply input voltages for the circuit **400** as well as control signals which operate switches in the circuit **300** and/or select capacitors from a bank of selectable capacitors.

In one embodiment, the capacitance measurement circuit **400** includes a differential amplifier **402** having an inverting input, connecting to a sensor electrode via a switch, a non-inverting input, and an output (V_{OUT}). A first switch **420** is coupled between the inverting input of the differential amplifier **402** and the sensor electrode, such as sensor electrodes **210**, **220** described above with respect to FIG. **2**, to which circuit **400** is coupled.

The differential amplifier **402** is configured as a charge integrator and includes a feedback capacitance (C_{FB}) coupled between the output and the inverting input of the differential amplifier. The feedback capacitance C_{FB} is represented by one or more capacitors, including a first feedback capacitor **404** (C_{FB0}) and a second feedback capacitor **406** (C_{FB1}), that are coupled on one side (e.g., a node **412**) to the output of the differential amplifier **402** and coupled on the other side (e.g., a node **410**) to the inverting input of the differential amplifier **402**. As described earlier, one capacitor **404** can be reset while the other capacitor **406** is pre-charged to either a supply voltage V_{RX} or ground during a pre-charge/reset phase of a sensing cycle. This pre-charge of the feedback capacitor works to cancel background capacitance.

The selection of whether the feedback capacitor **406** is pre-charged to the supply voltage or ground is accomplished by the position of a switch (omitted for simplicity) during the pre-charge/reset phase of a sensing cycle. A switch **408** is disposed in parallel to the feedback capacitors **404**, **406**, which operates as a reset mechanism to discharge and reset the feedback capacitors **404**, **406**.

In one embodiment, the capacitance measurement circuit **400** includes a first switch **422** and a second switch **424** configured between the feedback capacitor (e.g., C_{FB1}) and the output V_{OUT} of the differential amplifier **402** in series. In the embodiment depicted in FIG. **4**, the first switch **422** and the second switch **424** are transistors, although other equivalent circuit element(s) providing the described function may be utilized. That is, the first switch **422** and the second switch **424** may include one or more circuit elements have a resistance controllably by a switch. The capacitance measurement circuit **400** is configured to receive one or more control signals from a control module **426** or other component in the processing system **110**. In one embodiment, the control module **426** is configured to turn on the first switch **422**, thereby applying a first resistance value in series with feedback capacitor C_{FB1}. The control module **426** is further configured to, after a time delay, turn on the second switch **424**, placing a second resistance in parallel with the first resistance. In another embodiment, the control module **426** is configured to operate the first switch **422** into a linear mode causing a first resistance in the first switch **422**. The control module **426** can, after a time delay, operate the second switch **424** into a saturation mode causing a second resistance in the parallel to the first resistance.

FIG. **5** is a flow diagram illustrating a method **500** for measuring capacitance with a charge integrator, according to an embodiment. While the method **500** is described as being performed using the processing system **110** and the capacitance measurement circuits **400** described above, in addition to other similar system(s).

The method **500** begins at block **502**, where the processing system **110** resets a feedback capacitor of the capacitance measurement circuit **400** to a first voltage level. In some embodiment, the feedback capacitor is coupled between the first input of a differential amplifier **402** and an output of the differential amplifier **402**. In some embodiments, the processing system **110** operates a third switch (e.g., switch **314**) to connect the feedback capacitor to a voltage level (e.g., ground, reference voltage, supply voltage) during the reset phase and pre-charges the feedback capacitor to cancel at least some background capacitance (C_B).

At block **504**, the processing system **110** opens a plurality of switches between the feedback capacitor and the output of the differential amplifier **402**. In one embodiment, the processing system **110** opens the switches **422**, **424** coupled between the feedback capacitor **406** and the output V_{OUT} of the differential amplifier **402**. In some embodiments, the switch **422** and the switch **424** comprise transistors having a first, second, and third terminals, and the first terminals of the switches **422**, **424** are connected in parallel, and the second terminals of the switches **422**, **424** are connected in parallel. In some embodiments, the processing system **110** applies a control signal to the third terminals of the switches **422**, **424** to open the switches.

At block **506**, the processing system **110** couples a sensor electrode and the first input of the differential amplifier to initiate a measurement phase. In one embodiment, the processing system **110** closes the switch **420** to couple the sensor electrode **220** and the inverting input of the differential amplifier **402**, and initiates the measurement phase (also referred as the integrate phase).

At block **508**, the processing system **110** closes a first switch **422** of the plurality of switches between the feedback capacitor and the output of the differential amplifier. In one embodiment, the processing system **110** transmits a control signal to the first switch **422** to operate the switch **422** into a linear mode causing a first resistance for a first time duration. In some embodiments, the first resistance may be a relatively large resistance value and the switch **422** characterizing as a "weak switch."

At block **510**, the processing system **110** closes a remainder of the plurality of switches after a delay from closing the first switch. The time delay (e.g., T_{REACT}) may be preselected to provide the differential amplifier **402** with sufficient time to correct the input node of the differential amplifier **402** reference voltage level. In some embodiments, the processing system **110** transmits a control signal to the second switch **424** to operate the switch **424** into a saturation mode causing a second resistance in parallel to the first resistance. In some embodiments, the processing system **110** may use separate control signals where one control signal (e.g., "fb_conn_en_strong") is delayed by one or more clock cycles compared to the other control signal (e.g., "fb_conn_en"). In one implementation, the weak switch gate (e.g., switch **422**) may be controlled using a subset of bits (e.g., fb_conn_en<0:5>), whereas the strong switch (e.g., switch **424**) is controlled using a signal which is a result of an "AND" function between the fb_conn_en control signal and the fb_conn_en<0:5> control signal.

In one or more embodiments, the second resistance may be substantially less than the first resistance, making the effective resistance that is in series with the capacitor **306** to be small. In this way, the second switch **424** may be characterized as a "strong switch." As mentioned above, operating the first switch **422** into the linear mode causing the first resistance in the first switch **422** may increase the settling response of the capacitance measurement circuit **400**. This increase in settling response is only for a temporary amount of time because operating the second switch **424** into the saturation mode (sometimes referred to as the active mode) causing the second resistance in parallel to the first resistance may decrease the settling response of the capacitance measurement circuit, resulting in a substantially similar settling response of the capacitance measurement circuit than would exist without the switches **422**, **424**.

At block **512**, the processing system **110** operates the differential amplifier to integrate charge on the sensor electrode, such that an absolute capacitance corresponding to a coupling between the sensor electrode and an input object is measured. It should be recognized that the differential amplifier **402** may be operated in half-cycles, such that there is a first reset phase, a first integrate phase, then a second reset phase, and a second integrate phase in a single cycle.

In another embodiment of the present disclosure, the capacitance measurement circuit may be a switched capacitor circuit that utilizes existing digital control signals, and may not require additional, separate control signals. Circuits using such switching schemes reduce charge leakage into the integrator by preventing the input node of the integrator from going above and below supply rails, and also reduce current spikes on the supply. Such circuits are described in further detail below in conjunction with FIGS. **6**A-**6**D.

FIGS. **6**A-**6**D illustrate operation of a capacitance measurement circuit **600** through a cycle of absolute capacitive sensing, including a reset phase (FIG. **6**A) and an integration phase (FIG. **6**B-**6**D), according to an embodiment of the

present disclosure. The capacitance measurement circuit **600** may share common circuit elements and features as the capacitance measurement circuits **300**, **400** describe above. The capacitance measurement circuit **600** may be included as part of an input device **100** and/or the processing system **110**. For example, the processing system **110** may supply input voltages for the circuit **600** as well as control signals which operate switches in the circuit **600** and/or select capacitors from a bank of selectable capacitors.

In one embodiment, the capacitance measurement circuit **600** includes a differential amplifier **602** having a first (inverting, depicted as "−") input configured to be coupled to a sensor electrode (e.g., sensor electrodes **210**, **220**) for measuring capacitance from the sensor electrode. The differential amplifier **602** further includes a second (non-inverting, depicted as "+") input and an output (V_{OUT}). In some embodiments, a first switch **620** is disposed between the inverting input of the differential amplifier **602** and the sensor electrode.

The capacitance measurement circuit **600** further includes a first feedback capacitance **604** (C_{FB0}) coupled between the first input of the differential amplifier **602** and the output of the differential amplifier, and a second feedback capacitance **606** (C_{FB1}) coupled in parallel to the first feedback capacitance **606**. The second feedback capacitance **606** may include a plurality of capacitors in series with a plurality of associated switches. A switch **608** is disposed in parallel to the feedback capacitances **604**, **606**. The switch **608** operates as a reset mechanism to discharge and reset the feedback capacitances **604**, **606**. In FIGS. **6**A-**6**D, capacitance C_B represents a background capacitance between a sensor electrode and ground.

In the embodiment depicted in FIGS. **6**A-**6**D, feedback capacitance C_{FB} is split into multiple feedback capacitors, e.g., a first feedback capacitance (C_{FB0}) and a second feedback capacitance **306** (C_{FB1}) comprised of three capacitors (Cap**0**, Cap**1**, Cap**2**) arranged in parallel with associated switches **610**, **612**, **614**, respectively. The capacitance measurement circuit **600** may further include a plurality of pre-charge switches (similar to switch **314** of FIG. **3**A) coupled in parallel to the plurality of switches. In such an embodiment, each pre-charge switch is operable to connect the associated capacitor to a voltage level (e.g., V_{RX}, ground) during a reset phase and pre-charge the associated capacitor to cancel background capacitance. For example, one capacitor **604** can be reset while the other capacitors (Cap**0**, Cap**1**, Cap**2**) are pre-charged to either a reference voltage V_{RX} or ground during a pre-charge/reset phase of a sensing cycle. The depiction of the pre-charge switches in the circuit **600** have been omitted for clarify of illustration.

In some embodiments, the capacitance measurement circuit **600** includes a control module configured to operate the plurality of switches in reset phases and integrate phases to measure capacitance on the sensor electrode. As described in greater detail later, the control module is configured to, during an integrate phase, control each switch of the plurality of switches to couple the associated capacitor (e.g., Cap**0**, Cap**1**, Cap**2**) to the output (V_{OUT}) of the differential amplifier after a sequential delay. The sequential delay refers to changing of the state of one switch after a first delay, then changing the state of the next switch after a second delay, and so forth.

FIG. **6**A illustrates a reset phase of a (first half) sensing cycle. During this reset phase, the feedback capacitor (e.g., C_{FB0}) of the capacitance measurement circuit **600** is reset to a first voltage level. As show, the switch **620** is opened to decouple the circuit **600** from the sensor electrode, and the first feedback capacitance **604** is discharged by closing the switch **608**. In some embodiments, the processing system **110** opens a plurality of switches **610**, **612**, **614** between the feedback capacitance (Cap**0**, Cap**1**, Cap**2**) and the output of the differential amplifier **602**, and the plurality of capacitors Cap**0**, Cap**1**, Cap**2** are pre-charged to a voltage level by operating the pre-charge switches to be coupled to ground. During operation, controlling each switch of the plurality of switches to couple the associated capacitor to the output of the differential amplifier after the sequential delay reduces charge leakage in the first feedback capacitor when switching from a reset phase to the integrate phase.

FIGS. **6**B-**6**D illustrates the integration (measurement) phase of the (first half) sensing cycle. To initiate the measurement phase, the processing system **110** couples the sensor electrode and the first inverting input of the differential amplifier **602** by closing the switch **620**. Then, the processing system **110** closes a first switch of the plurality of switches between the feedback capacitor and the output V_{OUT} of the differential amplifier. As depicted in FIG. **6**B, the processing system **110** closes the first switch **610** associated with a first capacitor Cap**0** of the plurality of capacitors to couple the first capacitor Cap**0** between the non-inverting input and the output of the differential amplifier. The processing system **110** may begin operating the differential amplifier **602** to integrate charge on the sensor electrode, such that an absolute capacitance corresponding to a coupling between the sensor electrode and an input object is measured.

If all C_{FB1} capacitors are connected together at once when the integrate phase is initiated, there may be a large spike at the input node of the differential amplifier **602**. This scenario is depicted by the dashed line graph found in the inset in FIG. **6**B. Should the voltage level at the input node exceed the supply voltage level, charge leakage may occur. Charge may continue to leak until the charge is "leaked" below the turn-on point of diodes and switches, or until the differential amplifier **602** reacts and uses its feedback to set the input node to be equal to its positive terminal. Accordingly, not all of the feedback capacitors are connected to the output node at once at the start of the integration phase. For example, the processing system **110** closes the switch **610** (and leaves the other switches **612**, **614** open) to connect the capacitor Cap**0** to the output V_{OUT}. In some embodiments, the capacitors Cap**0**, Cap**1**, Cap**2** have a total capacitance less than or substantially equal to the feedback capacitance C_{FB0}. Because the single capacitor Cap**0** has a smaller capacitance than C_{FB0}, the input node of the differential amplifier **602** does not peak above supply due to charge sharing by the background capacitance C_B and the first feedback capacitance C_{FB0}. After some delay, depending on the slew rate and the bandwidth of the differential amplifier **602**, the differential amplifier **602** will eventually bring the input node back to V_{ref}. This behavior is depicted by the solid line graph found in the inset in FIG. **6**B, which has a substantially lower voltage peak than the dashed line graph of the conventional scenario.

In one embodiment, after a delay from closing the first switch **610**, the processing system **110** closes a remainder of the plurality of switches (e.g., switches **612**, **614**). As depicted in FIG. **6**C, the processing system **110** closes the switch **612** associated with the feedback capacitor Cap**1** to connect the capacitor Cap**1** between the inverting input and the output node of the differential amplifier (in parallel with the capacitor Cap**0** and the first feedback capacitance C_{FB0}). This operation may result in another peaking at the input node within the supply bounds of the differential amplifier,

as depicted in the inset in FIG. **6**C. Again, the differential amplifier brings the input node back to V_{ref}. FIG. **6**D depicts another stage of the integrate phase, where the processing system closes the switch **614** associated with the feedback capacitor Cap**2** to connect the capacitor Cap**2** between the inverting input and the output node.

In some embodiments, the processing system **110** may determine the sequential delay between closing of switches **610**, **612**, **614** based on a counter. The delay may be programmable and tracked using the counter. In one embodiment, the counter can be used to control the sequencing (i.e., which switch is the first, which switch is the second, etc.) and the instance (i.e., at what time) of coupling the capacitors Cap**0**, Cap**1**, Cap**2** to the output of the differential amplifier. In one example, a switching scheme may be utilized which connects Cap**0** at time t=0, then connects Cap**2** at time t=5 ns, and then connects Cap**1** at t=12 ns. In such a switching scheme, a the processing system **110** includes a "Counter **0**," which controls the switch of Cap**0** (i.e., switch **610**) that is programmed to count down to zero at t=0, a "Counter **1**" (which controls the switch **612** associated with Cap**1**) that is programmed to count down to zero at t=12 ns, and a "Counter **2**" (which controls the switch **615** associated with Cap**2**) that is programmed to count down to zero at t=5 ns.

While the present embodiment is described using three capacitors Cap**0**, Cap**1**, Cap**2**, it should be recognized that the described technique may be extended for N number of feedback capacitors to help reduce the current spikes at the supply.

It is further recognized that one variation of the described technique includes the division of capacitors into subsets. In an alternative embodiment, plurality of capacitors of the second feedback capacitance are arranged in subsets, and each subset is switched on at a same time during the integrate phase. In another variation of the described scheme, the processing system may select a "total" number of subsets. If the total number of subsets is M, then applying the described technique would yield M peaks at the input node of the charge integrator.

For example, in a capacitance measurement circuit **600** where the C_{FB1} (comprising Cap**0** and Cap**1**) has a total capacitance of 11 pF, and the first and second capacitors Cap**0**, Cap**1** have a capacitance of 3.8 pF, 7.2 pF, respectively. In a first scenario, Cap**0** is switched in at the start of the integration phase, and Cap**1** is switched in after a programmable delay. In this first scenario, the voltage peaking graph would have a second peak that is larger than a first voltage peak, because Cap**1** is a larger capacitance than Cap**0**. Contrast that behavior with a second scenario, in which Cap**1** is switched in at the start of integration, and Cap**0** is switched in after the programmable delay. In the second scenario, the first voltage peak would be larger than the second voltage peak. As such, the exact peak values may depend on a variety of factors, including the capacitance values relative to each other, in addition to C_B, C_{FB0}, and the speed of the differential amplifier.

Multi-Step Incremental Switching Techniques

As described earlier, another method for cancelling background capacitance is to add an opposite polarity charge on the background capacitance. FIG. **7** is a block diagram depicting a circuit **700** for generating a charge, according to one embodiment of the present disclosure. The circuit **700** includes a charge generation circuit **702**, a current conveyor **720**, and a current amplifier **730**. The charge generation circuit **702** is configured to generate a charge by driving one plate of a capacitor **716** (C**1**) from ground to a supply voltage to ground through a first resistor **704** (R**1**) and a buffer **710**.

The charge generated by the capacitor **716** is delivered to the current conveyor **720**. The input of the current conveyor **720** may be biased to the reference voltage. The current conveyor **720** includes one or more current mirrors to distribute current to multiple current amplifiers. The current amplifier(s) **706** is configured to amplify current by amplifier gain.

In conventional approaches, the current waveform at the input of the current conveyor **720** may be a decaying exponential waveform, having a time constant set by (R**1***C**1**). The peak current of the waveform is set by (V/R**1**), where V is the supply voltage. As such, the current waveform in traditional driving schemes can be represented by Equations 1 and 2 below.

$$I_{peak1} = \frac{V}{R1} \quad \text{(Equation 1)}$$

$$I(t) = I_{peak1} * e^{\frac{-t}{R1*C1}} \quad \text{(Equation 2)}$$

However, the problems of a traditional charge generation circuit are as follows. The peak current at the input of a current conveyor can easily be of mA order, and can be multiplied by the current amplifier (e.g., gain of 1 to 8). If multiple current amplifiers are working together at the same time, the summation of the peak current gets very large (hundreds of mA) and causes a large "bounce" on the internal power supply and ground line. Another problem of using the traditional waveform (which has a high amplitude and short duration) is that the waveform may not amplified accurately in the current amplifier because of the impulse nature of the waveform. The sharp waveform drives transistors to stay out of the saturation region and causes head room problems in the current conveyor. The result is that the output waveform may be distorted and causes an accuracy problem when the current is integrated by the charge integrator.

Accordingly, embodiments of the present disclosure provide a multi-step charge sharing technique that addresses such issues. The charge generation circuit **702** includes a second resistor **706** (R**2**), a third resistor **708** (R**3**), a switch **712** (SW**2**) and a switch **714** (SW**1**) arranged between the first resistor **704** and the capacitor **716**. In the embodiment shown in FIG. **7**, the second resistor **706** (R**2**) and the third resistor **708** (R**3**) are arranged in series with the first resistor **704**. The switch **712** (SW**2**) is arranged in parallel to the second resistor **706** and the other switch **714** (SW**1**) is arranged in parallel to the third resistor **708**.

In operation, at the beginning of charge generation, the switches **712** and **714** are opened and the peak current at the input of the current conveyor **720** can be represented by Equation 3 below. In some embodiments, the I_{peak2} represented in Equation 3 is smaller than I_{peak1} from Equation 1.

$$I_{peak2} = \frac{V}{(R1 + R2 + R3)} \quad \text{(Equation 3)}$$

In one or more embodiments, the processing system **110** may close the switches **712** and **714** sequentially with a time interval within a half cycle (t_{half}) of the input waveform

(e.g., square wave) and generate a waveform **800** depicted in FIG. **8**. That is, in a first step, the processing system **110** closes the switch **712** and leaves open the switch **714**. Then, in a second step, the processing system **110** closes the switch **714**. If the current waveform **800** is integrated from t=0 to $t=t_{half}$ the obtained results should be the same as those obtained via Equation 2.

In one or more embodiments, the described multi-step charge technique advantageously decreases the "bounce" in the supply and ground lines. The smaller "bounce" on the supply and ground line introduces less noise to the circuits which are connected to the same supply and ground lines. Secondly, due to the smaller peak amplitude (I_{peak2}), the accuracy can be improved when the charge is integrated by the charge integrator.

Switching Scheme for Charge Pump Circuits

While the switching scheme is described above in the context of a multi-step charge technique for global coarse baseline correction, it is understood that embodiments of the present disclosure can be extended for use in other types of circuits, particularly circuits that have operations which result in large swings in current and/or voltage levels. FIG. **9** depicts one such example.

FIG. **9** is a block diagram depicting a charge pump circuit **900** using the described switching scheme, according to one embodiment of the present disclosure. In the depicted charge pump circuit **900**, flyback capacitors Cf**1** and Cf**2** are charged and discharged to provide corresponding output voltages (CP_OUT).

In prior approaches, the switches in series with the flyback capacitors are large to reduce their resistance and thus the voltage drop across them. However, when these large switches are turned ON or OFF to charge or discharge the flyback capacitors, respectively, there may be large transient peaks in charging currents flowing across the circuit **900**. These high current peaks can result in high electromagnetic emission that affects neighboring sensitive circuits, integrated circuits, and/or processing systems within an input device. This issue can be especially acute in touch sensor ASICs used in mobile devices, where stringent requirements on peak emitted powers have to be met.

In one or more embodiments, instead of using conventional large switches, the charge pump circuit **900** includes a switching element comprised of multiple, weighted smaller switches (i.e., smaller relative to the single, large switch). The multiple switches are configured to turn on sequentially with a small delay within a charge pump clock cycle. In the embodiment depicted in FIG. **9**, the charge pump circuit **900** includes a switching element **902** that is connected in series with the flyback capacitor Cf**1** (i.e., to the bottom plate of Cf**1**), the switching element **902** being comprised of the multiple, weighted switches M**12**, M**13**, M**15**, M**16**. Another switching element **904** is coupled to the other flyback capacitor Cf**2**, and is comprised of the multiple, smaller switches M**18**, M**19**, M**20**, M**21** according to the embodiment illustrated in FIG. **9**.

In some embodiments, the delay between the smaller switches in a switching element **902** can be implemented using an RC circuit, or in other embodiments, can come from a counter. In the example depicted in FIG. **9**, the charge pump circuit **900** includes a RC delay circuit **910** coupled to the gates of switches M**12**, M**13**, M**15**, and M**16** to control the sequential delayed turning on and off of the switches. A similar RC delay circuit for the switching element **904** is omitted for simplicity of illustration.

Thus, the embodiments and examples set forth herein were presented in order to best explain the present invention and its particular application and to thereby enable those skilled in the art to make and use the invention. However, those skilled in the art will recognize that the foregoing description and examples have been presented for the purposes of illustration and example only. The description as set forth is not intended to be exhaustive or to limit the invention to the precise form disclosed.

What is claimed is:

1. A processing system for a capacitive sensing device, the processing system comprising:

a capacitance measurement circuit configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode, the capacitance measurement circuit comprising:

a differential amplifier having a first input coupled to the sensor electrode, a second input, and an output,

a feedback capacitor coupled between the first input of the differential amplifier and the output of the differential amplifier, and

a first switch and a second switch coupled between the feedback capacitor and the output of the differential amplifier in series; and

a control module configured to:

turn on the first switch and apply a first resistance in series with the feedback capacitor, and

after a time delay, turn on the second switch and place a second resistance in parallel with the first resistance, which lowers a total resistance in series with the feedback capacitor.

2. The processing system of claim **1**, wherein the first resistance in series with the feedback capacitor is greater than the second resistance.

3. The processing system of claim **1**, wherein the first switch and the second switch comprise transistors having a source terminal, a drain terminal, and a gate terminal, wherein the source terminals of the first and second switches are connected in parallel, and the drain terminals of the first and second switches are connected in parallel; and

wherein the control module is configured to apply different control signals to the gate terminals of the first and second switches.

4. The processing system of claim **1**, wherein turning on the first switch and applying the first resistance in series with the feedback capacitor increases a settling response of the capacitance measurement circuit, and

wherein turning on the second switch and placing the second resistance in parallel with the first resistance decreases the settling response of the capacitance measurement circuit.

5. The processing system of claim **1**, wherein the feedback capacitor is a first feedback capacitor, and the capacitance measurement circuit further comprises a second feedback capacitor in parallel with the first feedback capacitor and a third switch.

6. The processing system of claim **1**, wherein the capacitance measurement circuit further comprises a third switch operably to connect the feedback capacitor to a voltage level during a reset phase and pre-charge the feedback capacitor to cancel background capacitance.

7. The processing system of claim **1**, wherein turning on the first switch and applying the first resistance in series with the feedback capacitor reduces charge leakage in the feedback capacitor when switching from a reset phase to an integrate phase.

8. A processing system for a capacitive sensing device, the processing system comprising:

a capacitance measurement circuit configured to be coupled to a sensor electrode for measuring capacitance from the sensor electrode, the capacitance measurement circuit comprising:

a differential amplifier having a first input coupled to the sensor electrode, a second input, and an output,

a first feedback capacitance coupled between the first input of the differential amplifier and the output of the differential amplifier,

a second feedback capacitance coupled in parallel to the first feedback capacitance, the second feedback capacitance comprising a plurality of capacitors in series with a plurality of associated switches; and

a control module configured to, during an integrate phase, control each switch of the plurality of switches to couple the associated capacitor to the output of the differential amplifier after a sequential delay, and wherein the control module is configured to

turn on a first switch of the plurality of switches and apply a first resistance in series with a first capacitor of the capacitors associated with the plurality of switches, and

after a time delay, turn on a second switch of the plurality of switches and place a second resistance in parallel with the first resistance.

9. The processing system of claim **8**, wherein the plurality of capacitors comprising the second feedback capacitance are arranged in parallel.

10. The processing system of claim **8**, wherein the control module is configured to determine the sequential delay based a counter.

11. The processing system of claim **8**, wherein the control module is configured to, during the integrate phase, control each switch of the plurality of switches is further configured to:

close the first switch associated with the first capacitor of the plurality of capacitors to couple the first capacitor between the first input and the output of the differential amplifier, and

close a third switch associated with a second capacitor of the plurality of capacitors to couple the second capacitor between the first input and the output of the differential amplifier and in parallel with the first capacitor and the first feedback capacitance.

12. The processing system of claim **8**, wherein the plurality of capacitors of the second feedback capacitance are arranged in subsets, wherein each subset is switched on at a same time during an integrate phase.

13. The processing system of claim **8**, wherein the second feedback capacitance further comprises a plurality of pre-charge switches coupled in parallel to the plurality of switches, wherein each pre-charge switch is operably to connect the associated capacitor to a voltage level during a reset phase and pre-charge the associated capacitor to cancel background capacitance.

14. The processing system of claim **8**, wherein controlling each switch of the plurality of switches to couple the associated capacitor to the output of the differential amplifier after the sequential delay reduces charge leakage in the first feedback capacitance when switching from a reset phase to an integrate phase.

15. A method of capacitance measurement, the method comprising:

resetting a feedback capacitor of a capacitance measurement circuit to a first voltage level, wherein the feedback capacitor is coupled between a first input of a differential amplifier and an output of the differential amplifier;

opening a plurality of switches between the feedback capacitor and the output of the differential amplifier;

coupling a sensor electrode and the first input of the differential amplifier to initiate a measurement phase;

closing a first switch of the plurality of switches between the feedback capacitor and the output of the differential amplifier, closing the first switch apply a first resistance in series with the feedback capacitor;

after a time delay, turn on a second switch of the plurality of switches and place a second resistance in parallel with the first resistance;

closing a remainder of the plurality of switches after a delay from closing the first switch; and

operating the differential amplifier to integrate charge on the sensor electrode, such that an absolute capacitance corresponding to a coupling between the sensor electrode and an input object is measured.

16. The method of claim **15**, wherein resetting the feedback capacitor of the capacitance measurement circuit to the first voltage level further comprises:

operating a pre-charge switch to couple the feedback capacitor to a second voltage level and pre-charge the feedback capacitor for background capacitance cancellation.

17. The method of claim **15**, wherein the first and second switches of the plurality of switches between the feedback capacitor and the output of the differential amplifier comprises:

a first transistor and a second transistor having a first, second, and third terminals, wherein the first terminals of the first and second switches are connected in parallel, and the second terminals of the first and second switches are connected in parallel, wherein the first and second transistors are configured to receive control signals on the third terminals of the first and second transistors.

18. The method of claim **15**, wherein closing the first switch of the plurality of switches between the feedback capacitor and the output of the differential amplifier further comprises:

operating the first switch into a linear mode causing a first resistance in the first switch, and

wherein closing the remainder of the plurality of switches after the delay from closing the first switch further comprises:

operating the second switch into a saturation mode causing a second resistance in parallel to the first resistance, wherein the first resistance is greater than the second resistance.

19. The method of claim **15**, wherein the feedback capacitor comprises a plurality of feedback capacitors, wherein each of the plurality of feedback capacitors is arranged in series with an associated switch of the plurality of switches.

20. The method of claim **15**, wherein each switch of the plurality of switches between the feedback capacitor and the output of the differential amplifier is configured to couple the associated feedback capacitor between the first input of the differential amplifier and the output of the differential amplifier.

* * * * *